

Emergency Light Fittings for Fluorescent Lamps

Series ECOLUX 6608



www.stahl.de



- > For fluorescent lamps 2 x 18 W and 2 x 36 W
- > For emergency light operation periods of 1.5 or 3 hrs
- > During emergency time:
If emergency lamp broken changing to the other lamp
- > Battery case which can be opened separately for easy change of batteries by means of plug-type contacts
- > Enclosure closed by means of quick-action locks

E2



09379E00

The single-battery-supplied emergency lamps of the Series ECOLUX 6608 lighting are employable as safety lighting in accordance EN 60598.

ATEX/IECEX							NEC 505							NEC 506							NEC 500						
							Class I														Class I		Class II		Class III		
Zone	0	1	2	20	21	22	Zone	0	1	2	20	21	22	Division	1	2	1	2	1	2							
For use in			x		x	x	For use in			x				For use in		x	x	x	x	x							

WebCode 6608B

Emergency Light Fittings for Fluorescent Lamps

Series ECOLUX 6608

Selection Table

Version	Lamps	Lamp activation	Order number	Weight kg
ECOLUX 6608 Zone 2, 21, 22	2 x 18 W	2-channel	6608/522-9..1-7247	6.500
	2 x 36 W	2-channel	6608/542-9..1-7247	8.000
Order Number Supplement				
Through wiring	without (standard)		6608 / ...-0.-....	
	Special: With 6-cores		6608 / ...-6.-....	
Cable entries	Standard: M25 x 1.5 1 Cable gland 2 Stopping plugs		6608 / ...-1.-....	
	Special M20 or M25 of moulded material or metal to be specified with order		6608 / ...-9.-....	
Note	The lights are delivered without fluorescent lamps and assembly parts. These parts must be ordered separately!			

Explosion protection

Explosion protection

Global (IECEX)
Gas and dust

IECEX BVS 11.0032X
EX nA IIC T4 Gc or EX nAc IIC T4
Ex tb IIIC T90°C Db or Ex tb IIIC T90°C
Ex tc IIIC T90°C DC or Ex tc IIIC T90°C

Europe (ATEX)
Gas

BVS 03 E 093 X
⚠ II 3 G Ex nA IIC T4 Gc or ⚠ II 3 G Ex nAc IIC T4

Dust

BVS 03 ATEX E 094 X
⚠ II 2D Ex tb IIIC T90°C Db or ⚠ II 2D Ex tb IIIC T90°C

* T90 °C = max. surface temperature referred to 18 W, 36 W; Ta = + 40 °C

Certifications and certificates

Certificates

ATEX, IECEX, United Staates of America (FM), Canada (CSA), Belarus (operating licence)

Technical Data

Electrical data

Rated voltage

220 V ... 254 V; 50/60 Hz for lamps acc EN60081
110 V ... 127 V; 50/60 Hz for lamps acc EN60081
120V; 50/60 Hz for lamps acc ANSI (IECEX only)

Disconnection of the light

Optionally

when opening the lamp
cover

when opening the locking mechanism on one of the quick-action locks,
all poles of the voltage supply to the ballast are disconnected;
contacts of the switching element with positive break, they are switched
on again as soon as the lamp cover and the quick-action lock are
closed.

in case of a lamp fault

in case of a lamp fault, the electronic ballast disconnects the defective
lamp from the power supply.

Luminous Characteristics

Lamps

2 x 17/18 W

2 x 32/36 W

Lamp version

2-lamp

2-lamp

without auxiliary reflector

with auxiliary reflector

Class according to LitG

B21

B31

Emergency Light Fittings for Fluorescent Lamps

Series ECOLUX 6608

STAHL

E2

Technical Data

Measures for light guidance	Standard Broad reflective, internal reflector of light fitting painted white. Colour: Signal white RAL 9003; lateral glare is limited by the lamp diffuser cover. Special Auxiliary reflector (easily mountable), narrow-angle / wide-angle shining, aluminium anodised and polished.
-----------------------------	---

Ambient conditions

Standard operation	- 20 ... + 50 °C
Battery operated	- 5 ... + 50 °C charge - 20 ... + 50 °C discharge

Mechanical data

Degree of protection	IP66 (IP64 with Breather 8162)
Protection class	I (with internal PE connection)
Material	
Enclosure	Polyester resin, glass fibre reinforced, colour white, similar to RAL 9010
Lamp cover	Polycarbonate, shock-resistant, as an option an aromatic-resistant paint can be used
Seal	Silicone foam gasket in the lamp cover
Quick-acting locks	Polyamide, glass fibre reinforced
Assembly parts	Polyester resin, glass fibre reinforced, white, similar to RAL 9010
Cover options	Quick-acting locks to be opened by means of a screwdriver; lamp cover is equipped with a hinge

Assembly / Installation

Cable glands	Connection side: 1 cable gland M25 x 1.5 and 1 stopping plug M25 x 1.5 Opposite side: 1 stopping plug M25 x 1.5 (cable glands enclosed) Entry parts in moulded plastic (8161/8290): M20 Metal glands: M20, M25, Metal cable gland earthing via metal adapter plates
Connection option	Terminals L1, L2, L3, N, PE, L' (switched phase) 2.5 mm ² fine / single wire L1 = charging phase, must not be switched
Through wiring	Lights available with internal through wiring, 6 wires; Cross-section 2.5 mm ² for max. 16 A only possible for 36 W

Battery set

Version	NiCd battery, gas-tight, the battery housing mounted on the lamp
Capacity	7 Ah
Operating voltage	6 V
Replacing the battery set	Open the battery housing; After loosening one of the plug contacts, the battery unit can be removed from the housing.

Emergency light electronics

Operating modes	Maintained operation, stand-by operation, emergency blocking			
Battery charge	intelligent battery management system, microprocessor-based (on-load time of max. 14 h) deep-discharging protection to the avoidance of cell pol reversal			
Emergency light mode	During emergency light operation only one more lamp is operated. This results in reduced lighting power (see emergency light operation time)			
Emergency light service time	Battery capacity	Emergency light operation time	Emergency light power	
			17/18 W light fitting	32/36 W light fitting
	7 Ah	1.5 h	100 %	60 %
		3 h	60 %	30 %
Switchover voltage	from mains to battery operation for $U < 0.74 \times U_N$ from battery to mains operation for $U > 0.80 \times U_N$			
Test functions				
Functional test	Check the emergency light function once a week. First test 1 hour after commissioning. During the first test, both lamps are switched on for 1 minute and the battery is charged with the rated current. Battery error and lamp fault are detected and indicated by means of the LED.			
Light duration test of the emergency lighting	Test of the battery capacity in time intervals of 12 months; operation of the device in the emergency light mode during 2/3 of rated operation time. If the light is switched off by the discharge protection before the time has elapsed, the battery cannot be used for the emergency mode. The red LED indicates the error.			






Emergency Light Fittings for Fluorescent Lamps

Series ECOLUX 6608

STAHL

E2


Accessories and Spare Parts

Designation	Illustration	Description	Art. no.	Weight kg
Fluorescent lamp	 04936E00	Two-pin cap $\varnothing$ 26 mm Light colour: universal white		0.000
		18 W 1350 lm	108952	0.100
		36 W 3350 lm	108951	0.200
		58 W 5200 lm	108950	0.220
Diffuser cover	 05329E00	for lamp 18 / 20 W	124635	0.500
		for lamp 36 / 40 W	124646	1.300
		for lamp 58 / 65 W	124657	1.000
Switch	 10809E00	Switching element 8080/1-3-L, 2 normally closed contacts	132527	0.025
Lamp-holder	 05888E00	Lamp holder for two-pin cap lamps G 13	107275	0.008
Mounting rail	 05895E00	for a variable mounting distance of 1 pair	124894	0.210
Mounting clamp bracket	 05896E00	Mounting bracket mounted on the mounting rail for a variable mounting distance	124901	0.300
M8 ring bolts	 05378E00	M8, direct mounting in insert nuts, 1 pair	115736	0.120
Wall-mounting bracket	 05460E00	to mount the lamps as side-entry lamps using a tube with a length of 1300 mm, $\varnothing$ 42 mm		0.000
		(for pipe clamp R 1 1/2")	109281	6.000
Ceiling mounting bracket	 05897E00	for ceiling suspension of the lamp, 1 pair	124908	0.230
Pipe clamps	 09402E00	with mounting rail for a variable mounting distance; Material: stainless steel		0.000
		R 1 1/4" ($\varnothing$ 42 mm)	124913	1.140
		R 1 1/2" ($\varnothing$ 48 mm)	124891	1.160
		R 2" ($\varnothing$ 60 mm)	124898	1.300
Mounting set „Grid cable rack”	 04361E00	for grid cable racks, with a cable diameter of 6 mm; with mounting rail for a variable mounting distance; Material: stainless steel	124905	1.560
Ceiling and wall-mounting bracket	 05898E00	mounted on a mounting rail for a variable mounting distance; Material: stainless steel Lamp can be swiveled in steps of 15°		0.000
		1 pair	124910	1.150

Emergency Light Fittings for Fluorescent Lamps

Series ECOLUX 6608

Accessories and Spare Parts


Designation	Illustration	Description	Art. no.	Weight kg
Adapter plates	 05755E00	for earth continuity when using metal glands;		0.000
		1 x M20 x 1.5 1 piece	115815	0.070
		1 x M25 x 1.5 1 piece	115818	0.070
		1 x NPSM 1/2" 1 piece	115821	0.070
		1 x NPT 3/4" 1 piece	115824	0.070
		2 x M20 x 1.5 1 piece	115826	0.060
		2 x M25 x 1.5 1 piece	115828	0.060
		2 x NPSM 1/2" 1 piece	115829	0.060
Battery unit	 10321E00	NiCd-battery for 6608/5 7 Ah / 6 V 1 pc	118017	1.150
Reflectors	 05324E00	for later installation, broad deep beam		0.000
		for lights with two lamps 18 W	117098	0.265
Cable gland	 05864E00	for lights with two lamps 36 W	117115	0.234
		of moulded material, series 8161		0.000
		8161/5-M20-13 1 piece	138518	0.012
		8161/5-M20-13 50 pieces	138454	0.600
		8161/5-M25-17	138520	0.020
Stopping plug	 04840E00	8161/5-M25-17 50 pieces	138456	1.000
		of moulded material, series 8290		0.000
		8290/3-M20 1 piece	143522	0.005
		8290/3-M20 100 pieces	143543	0.500
		8290/3-M25	143524	0.007
Breathing gland	 05703E00	8290/3-M25 100 pieces	143544	0.700
		for installation in lights; in moulded material; without counter nut		0.000
		Thread: M25 x 1.5 1 pc	138573	0.010
		Thread: M25 x 1.5 20 pcs	138576	0.200

Emergency Light Fittings for Fluorescent Lamps


Series ECOLUX 6608

STAHL

Dimensional Drawings (All Dimensions in mm) - Subject to Alterations



Emergency light fittings ECOLUX 6608, 18 W, 36 W



Installation accessories

We reserve the right to make alterations to the technical data, dimensions, weights, designs and products available without notice. The illustrations cannot be considered binding.